

UNITED STATES PATENT APPLICATION FOR:

APPARATUS AND METHOD FOR ALLOCATING BITS TEMPORALY
BETWEEN FRAMES IN A CODING SYSTEM

INVENTORS:

JUNGWOO LEE

ATTORNEY DOCKET NUMBER: SAR 13700

CERTIFICATION OF MAILING UNDER 37 C.F.R. 1.10

I hereby certify that this New Application and the documents referred to as enclosed therein are being deposited with the United States Postal Service on 4/19/01, in an envelope marked as "Express Mail United States Postal Service", Mailing Label No. EL41648713US addressed to: Assistant Commissioner for Patents, Box PATENT APPLICATION, Washington, D.C. 20231.

Signature

Name

Date of signature

THOMASON, MOSER & PATTERSON LLP
595 Shrewsbury Ave.
Shrewsbury, New Jersey 07702
(732)530-9404

APPARATUS AND METHOD FOR ALLOCATING BITS TEMPORALLY BETWEEN FRAMES IN A CODING SYSTEM

GOVERNMENT RIGHTS IN THIS INVENTION

[0001] This invention was made with U.S. government support under contract number NIST contract 70NANB5H1178. The U.S. government has certain rights in this invention.

[0002] The present invention relates to an apparatus and concomitant method for optimizing the coding of an image sequence, e.g., motion video. More particularly, this invention relates to a method and apparatus that temporally allocates bits (i.e., bit budget) between frames of an image sequence to be encoded by a coding system.

BACKGROUND OF THE INVENTION

[0003] The increasing development of digital video technology presents an ever increasing problem of reducing the high cost of video compression codecs (coder/decoder) and resolving the inter-operability of equipment of different manufacturers. To achieve these goals, the Moving Picture Experts Group (MPEG) created international standards 11172 and 13818, which are incorporated herein in their entirety by reference.

[0004] In the area of rate control, MPEG does not define a specific algorithm for controlling the bit rate of an encoder. It is the task of the encoder designer to devise a rate control process for controlling the bit rate such that the decoder input buffer neither overflows nor underflows. Thus, it is the task of the encoder to monitor the number of bits generated by the encoder, thereby preventing the overflow and underflow conditions.

[0005] Currently, one way of controlling the bit rate is to alter the quantization process, which will affect the distortion of the input video image. By altering the quantizer scale, the bit rate can be changed and controlled. Although changing the quantizer scale is an effective method of implementing the rate control of an encoder,

it has been shown that a poor rate control process will actually degrade the visual quality of the video image.

[0006] In the current MPEG coding strategies, the quantizer scale for each macroblock is selected by assuming that all the pictures of the same type have identical complexity within a group of pictures. However, the quantizer scale selected by this criterion may not achieve optimal coding performance, since the complexity of each picture will vary with time.

[0007] Furthermore, encoders that utilize global-type transforms have similar problems. For example, one such global-type compression technique appears in the Proceedings of the International Conference on Acoustics, Speech and Signal Processing, San Francisco, Cal. March 1992, volume IV, pages 657-660, where there is disclosed a signal compression system which applies a hierarchical subband decomposition, or wavelet transform, followed by the hierarchical successive approximation entropy-coded quantizer incorporating zerotrees. The representation of signal data using a multiresolution hierarchical subband representation was disclosed by Burt et al. in IEEE Trans. on Commun., Vol Com-31, No. 4, April 1983, page 533. A wavelet pyramid, also known as critically sampled quadrature-mirror filter (QMF) subband representation, is a specific type of multiresolution hierarchical subband representation of an image. A wavelet pyramid was disclosed by Pentland et al. in Proc. Data Compression Conference Apr. 8-11, 1991, Snowbird, Utah. A QMF subband pyramid has been described in "Subband Image Coding", J.W. Woods ed., Kluwer Academic Publishers, 1991 and I. Daubechies, Ten Lectures on Wavelets, Society for Industrial and Applied Mathematics (SIAM): Philadelphia, Pa., 1992. Furthermore, U.S. patent 5,412,741 issued May 2, 1995 and herein incorporated by reference discloses an apparatus and method for encoding information with a high degree of compression.

[0008] The output bit stream from a video encoder tends to have a variable bit rate that fluctuates according to scene contents and the nature of the coding process used by the encoder. As such, the encoder requires a mechanism to regulate the output bit rate to match the channel rate with minimum loss of signal quality.

[0009] Therefore, a need exists in the art for an apparatus and method to maintain the overall quality of the video image while optimizing the coding rate. Similarly, encoders that utilize global-type transforms such as wavelet transforms have special requirements that are not met by the prior art rate control techniques.

SUMMARY OF THE INVENTION

[0010] The present invention is a method and apparatus for temporally allocating bits between frames of an image sequence in a coding system such that temporal fluctuations are smoothed out. Namely, a picture quality is monitored on a frame by frame basis. In one embodiment, an average distortion measure is derived from several previous picture frames and this temporal average distortion measure is compared to the distortion measure of a current frame. The difference of this comparison is measured against a predefined threshold, where the result is used to control the bit allocation for the current frame. In an alternative embodiment, the present method is applied in conjunction with a wavelet transform.

BRIEF DESCRIPTION OF THE DRAWINGS

[0011] The teachings of the present invention can be readily understood by considering the following detailed description in conjunction with the accompanying drawings, in which:

[0012] FIG. 1 illustrates a block diagram of the apparatus of the present invention;

[0013] FIG. 2 illustrates a flowchart for a rate control method according to the invention;

[0014] FIG. 3 depicts a block diagram of a wavelet-based encoder incorporating the present invention;

[0015] FIG. 4 is a graphical representation of a wavelet tree; and

[0016] FIG. 5 illustrates an encoding system of the present invention.

[0017] To facilitate understanding, identical reference numerals have been used, where possible, to designate identical elements that are common to the figures.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT

[0018] FIG. 1 depicts a block diagram of the apparatus 100 of the present invention for using a picture quality or distortion measure to temporally allocate bits in an encoding system. In the preferred embodiment of the present invention, the apparatus 100 is an encoder or a portion of a more complex block-based motion compensation coding system. The apparatus 100 comprises a motion estimation module 140, a motion compensation module 150, a rate control module 130, a DCT module 160, a quantization (Q) module 170, a variable length coding (VLC) module 180, a buffer 190, an inverse quantization (Q^{-1}) module 175, an inverse DCT (DCT^{-1}) transform module 165, a subtractor 115 and a summer 155. Although the apparatus 100 comprises a plurality of modules, those skilled in the art will realize that the functions performed by the various modules are not required to be isolated into separate modules as shown in FIG. 1. For example, the set of modules comprising the motion compensation module 150, inverse quantization module 175 and inverse DCT module 165 is generally known as an "embedded decoder".

[0019] FIG. 1 illustrates an input video image (image sequence) 110 which is digitized and represented as a luminance and two color difference signals (Y , C_r , C_b) in accordance with the MPEG standards. These signals are further divided into a plurality of layers (sequence, group of pictures, picture, slice, macroblock and block) such that each picture (frame) is represented by a plurality of macroblocks. Each macroblock comprises four (4) luminance blocks, one C_r block and one C_b block where a block is defined as an eight (8) by eight (8) sample array. The division of a picture into block units improves the ability to discern changes between two successive pictures and improves image compression through the elimination of low amplitude transformed coefficients (discussed below). The digitized signal may optionally undergo preprocessing such as format conversion for selecting an appropriate window, resolution and input format.

[0020] The input video image on path 110 is received into motion estimation module 140 for estimating motion vectors. A motion vector is a two-dimensional vector which is used by motion compensation to provide an offset from the coordinate position of a block in the current picture to the coordinates in a reference frame.

Because of the high redundancy that exists between the consecutive frames of a video image sequence, a current frame can be reconstructed from a reference frame and the difference between the current and reference frames by using the motion information (motion vectors). The reference frames can be a previous frame (P-frame), or previous and/or future frames (B-frames). The use of motion vectors greatly enhances image compression by reducing the amount of information that is transmitted on a channel because only the changes between the current and reference frames are coded and transmitted. Various methods are currently available to an encoder designer for implementing motion estimation.

[0021] The motion vectors from the motion estimation module 140 are received by the motion compensation module 150 for improving the efficiency of the prediction of sample values. Motion compensation involves a prediction that uses motion vectors to provide offsets into the past and/or future reference frames containing previously decoded sample values that are used to form the prediction error. Namely, the motion compensation module 150 uses the previously decoded frame and the motion vectors to construct an estimate of the current frame. Furthermore, those skilled in the art will realize that the functions performed by the motion estimation module and the motion compensation module can be implemented in a combined module, e.g., a single block motion compensator.

[0022] Furthermore, prior to performing motion compensation prediction for a given macroblock, a coding mode must be selected. In the area of coding mode decision, MPEG provides a plurality of different macroblock coding modes. Generally, these coding modes are grouped into two broad classifications, inter mode coding and intra mode coding. Intra mode coding involves the coding of a macroblock or picture that uses information only from that macroblock or picture. Conversely, inter mode coding involves the coding of a macroblock or picture that uses information both from itself and from macroblocks and pictures occurring at different times. Specifically, MPEG-2 provides macroblock coding modes which include intra mode, no motion compensation mode (No MC), frame/field/dual-prime motion compensation inter mode, forward/backward/average inter mode and field/frame DCT mode. The proper selection of a coding mode for each macroblock will improve

coding performance. Again, various methods are currently available to an encoder designer for implementing coding mode decision.

[0023] Once a coding mode is selected, motion compensation module 150 generates a motion compensated prediction (predicted image) on path 152 of the contents of the block based on past and/or future reference pictures. This motion compensated prediction on path 152 is subtracted via subtractor 115 from the video image on path 110 in the current macroblock to form an error signal or predictive residual signal on path 153. The formation of the predictive residual signal effectively removes redundant information in the input video image. Namely, instead of transmitting the actual video image via a transmission channel, only the information necessary to generate the predictions of the video image and the errors of these predictions are transmitted, thereby significantly reducing the amount of data needed to be transmitted. To further reduce the bit rate, predictive residual signal on path 153 is passed to the DCT module 160 for encoding.

[0024] The DCT module 160 then applies a forward discrete cosine transform process to each block of the predictive residual signal to produce a set of eight (8) by eight (8) block of DCT coefficients. The discrete cosine transform is an invertible, discrete orthogonal transformation where the DCT coefficients represent the amplitudes of a set of cosine basis functions. One advantage of the discrete cosine transform is that the DCT coefficients are uncorrelated. This decorrelation of the DCT coefficients is important for compression, because each coefficient can be treated independently without the loss of compression efficiency. Furthermore, the DCT basis function or subband decomposition permits effective use of psychovisual criteria which is important for the next step of quantization.

[0025] The resulting 8 x 8 block of DCT coefficients is received by quantization module 170 where the DCT coefficients are quantized. The process of quantization reduces the accuracy with which the DCT coefficients are represented by dividing the DCT coefficients by a set of quantization values with appropriate rounding to form integer values. The quantization values can be set individually for each DCT coefficient, using criteria based on the visibility of the basis functions (known as

visually weighted quantization). Namely, the quantization value corresponds to the threshold for visibility of a given basis function, i.e., the coefficient amplitude that is just detectable by the human eye. By quantizing the DCT coefficients with this value, many of the DCT coefficients are converted to the value "zero", thereby improving image compression efficiency. The process of quantization is a key operation and is an important tool to achieve visual quality and to control the encoder to match its output to a given bit rate (rate control). Since a different quantization value can be applied to each DCT coefficient, a "quantization matrix" is generally established as a reference table, e.g., a luminance quantization table or a chrominance quantization table. Thus, the encoder chooses a quantization matrix that determines how each frequency coefficient in the transformed block is quantized.

[0026] However, subjective perception of quantization error greatly varies with the frequency and it is advantageous to use coarser quantization values for the higher frequencies. Namely, human perceptual sensitivity of quantization errors are lower for the higher spatial frequencies. As a result, high frequencies are quantized more coarsely with fewer allowed values than low frequencies. Furthermore, an exact quantization matrix depends on many external parameters such as the characteristics of the intended display, the viewing distance and the amount of noise in the source. Thus, it is possible to tailor a particular quantization matrix for an application or even for an individual sequence of frames. Generally, a customized quantization matrix can be stored as context together with the compressed video image. The proper selection of a quantizer scale is performed by the rate control module 130.

[0027] Next, the resulting 8 x 8 block of quantized DCT coefficients is received by variable length coding module 180 via signal connection 171, where the two-dimensional block of quantized coefficients is scanned in a "zig-zag" order to convert it into a one-dimensional string of quantized DCT coefficients. This zig-zag scanning order is an approximate sequential ordering of the DCT coefficients from the lowest spatial frequency to the highest. Since quantization generally reduces DCT coefficients of high spatial frequencies to zero, the one-dimensional string of

quantized DCT coefficients is typically represented by several integers followed by a string of zeros.

[0028] Variable length coding (VLC) module 180 then encodes the string of quantized DCT coefficients and all side-information for the macroblock such as macroblock type and motion vectors. The VLC module 180 utilizes variable length coding and run-length coding to efficiently improve coding efficiency. Variable length coding is a reversible coding process where shorter code-words are assigned to frequent events and longer code-words are assigned to less frequent events, while run-length coding increases coding efficiency by encoding a run of symbols with a single symbol. These coding schemes are well known in the art and are often referred to as Huffman coding when integer-length code words are used. Thus, the VLC module 180 performs the final step of converting the input video image into a valid data stream. Those skilled in the art will realize that the VLC module can be replaced with other types of entropy coders.

[0029] The data stream is received into a "First In-First Out" (FIFO) buffer 190. A consequence of using different picture types and variable length coding is that the overall bit rate into the FIFO is variable. Namely, the number of bits used to code each frame can be different. In applications that involve a fixed-rate channel, a FIFO buffer is used to match the encoder output to the channel for smoothing the bit rate. Thus, the output signal of FIFO buffer 190 is a compressed representation of the input video image on path 110, where it is sent to a storage medium or telecommunication channel via path 295.

[0030] The rate control module 130 serves to monitor and adjust the bit rate of the data stream entering the FIFO buffer 190 to prevent overflow and underflow on the decoder side (within a receiver or target storage device, not shown) after transmission of the data stream. Thus, it is the task of the rate control module 130 to monitor the status of buffer 190 to control the number of bits generated by the encoder.

[0031] In the preferred embodiment of the present invention, rate control module 130 monitors picture quality frame by frame using a picture quality measure. Namely,

by carefully monitoring the picture quality of a plurality of immediately previous frames, a temporal bit allocation method can adaptively allocate a bit budget to a current frame; i.e., assigning and/or modifying a target bit rate for a current frame. For example, bits are temporally allocated for each picture type in accordance to the MPEG standard. In one embodiment, quality measures are derived for a number of immediate previous frames (e.g., three or more) for each frame type (e.g., I, P, or B frames). An average is derived from these quality measures and a current measure for a current frame is subtracted from the derived average and the difference is compared to a threshold value. The result from the comparison is used to control the allocation of bits for a current frame. In turn, a quantizer scale is selected for each macroblock such that target bit rate for a current picture is achieved while an optimal quantization scale ratio is maintained for successive macroblocks to produce a uniform visual quality over the entire picture.

[0032] Specifically, the rate control module 130 initially obtains a rough estimate of the complexity of a specific type of picture (I, P, B) from previously encoded pictures or by calculating the frame level target rate T_I , T_P and T_B for each frame type I frame, B frame and P frame e.g., using the TM4 and TM5 models of the MPEG standard. This estimated complexity is used to derive a predicted number of bits necessary to code each macroblock. With this knowledge, a quantizer scale is calculated for the macroblock in accordance with a complexity model having a polynomial form. This complexity model is derived to meet the constraint that the selected quantizer scales for the macroblocks should approach the target bit rate for the picture.

[0033] Furthermore, the quantizer scale is optionally refined by a modifier which is derived to meet a constraint that requires a constant visual quality to be maintained for the entire picture. Namely, the constraint requires an optimal quantization scale ratio to be maintained for successive macroblocks. The rate control module applies the modifier to the quantizer scale to produce an optimal quantizer scale which is used to code the macroblock. Once the macroblock is encoded, the rate control module recursively adjusts the complexity model through the use of a polynomial regression process. That is, the actual number of bits necessary to code the macroblock is used to refine the complexity model so as to improve the prediction of

a quantizer scale for the next macroblock. A detailed description of such quantizer scale selection method is disclosed in U.S. patent 6,160,846 issued December 12, 2000, which is incorporated herein by reference.

[0034] Returning to FIG. 1, the resulting 8 x 8 block of quantized DCT coefficients from the quantization module 170 is also received by the inverse quantization module 175 via signal connection 172. At this stage, the encoder regenerates I-frames and P-frames of the input video image by decoding the data so that they are used as reference frames for subsequent encoding. The inverse quantization module 175 starts the decoding process by dequantizing the quantized DCT coefficients. Namely, the quantized DCT coefficients are multiplied by a set of quantization values with appropriate rounding to produce integer values.

[0035] The resulting dequantized 8 x 8 block of DCT coefficients are passed to the inverse DCT module 165 where inverse DCT is applied to each macroblock to produce the decoded error signal. This error signal is added back to the prediction signal from the motion compensation module via summer 155 to produce a decoded reference picture (reconstructed image). Generally, if an I-frame or a P-frame is decoded, it will be stored, replacing the oldest stored reference. Thus, an apparatus 100 for temporally allocating bits between I, P and B frames such that a picture quality measure can be used to smooth out temporal fluctuations is disclosed.

[0036] It should be noted that although the present invention is disclosed in view of the MPEG standards, the present invention is not so limited. Specifically, the present invention can be employed in other encoders that are compliant to other standards e.g., ATSC, and the like.

[0037] FIG. 2 illustrates a flowchart for a rate control method 200 according to the invention. The method 200 begins at step 205 and proceeds to step 210 where the method computes or acquires quality measures for the three previous frames of the same type. Namely, three picture quality measures " D_i " where $i=1, 2$ and 3 are computed for previous I, P and B frames. For example, if a current frame is to be encoded as an I-frame, then the picture quality measures for the three immediate previous I-frames are used. Similarly, if a current frame is to be encoded as a P-

frame, then the picture quality measures for the three immediate previous P-frames are used.

[0038] In one embodiment, as discussed below, the picture quality measure is a just noticeable difference (JND) measure. An example of a description of a just noticeable difference measure can be found in U.S. patent 5,694,491, issued December 2, 1997, which is incorporated herein by reference. However, it will be appreciated by those skilled in the art that although the invention is discussed in the context of JND, other picture quality measures may be used i.e., peak signal-to-noise ratio (PSNR) and mean square error (MSE). It will also be appreciated that an average of three measures is only an example. The invention can be adapted to three or more average measures or two average measures.

[0039] The method 200 computes, at step 215 the average distortion or average picture quality as:

$$D_{AVG} = \frac{D_1 + D_2 + D_3}{3} \quad (1)$$

[0040] At step 220, the method queries whether $D_i - D_{AVG}$ is greater than a threshold value, "Th" where in a preferred embodiment Th is set to 0.5 JND and D_i a quality measure is for a current frame. The difference between $D_i - D_{AVG}$ is a resultant value "R". If the query is positively answered e.g., if $R > Th$, then method 200 proceeds to step 225 where the bit budget for a current frame is increased. The bit rate is increased because the projected distortion under a current target bit rate for the current frame will be greater by at least the threshold value as compared to at least three immediate previous frames of the same type. Thus, to reduce such a "spike" in distortion for the current frame, the bit budget is increased for the current frame to allow the encoder sufficient resources to reduce the distortion, e.g., reduce the size of the quantizer scale. If the query is negatively answered, then method 200 proceeds to step 230.

[0041] It should be noted that an initial bit budget can be acquired using traditional methods, e.g., TM4 and TM5 of the MPEG standard. Namely, the present invention can be adapted into existing encoders as a refinement module to more accurately predict or allocate bits between frames.

[0042] At step 230, method 200 queries whether $D_i - D_{AVG}$ is less than the threshold value "Th". If the query is positively answered, e.g., if $R < Th'$ where $Th' < 0$, then method 200 proceeds to step 235 where the bit budget for a current frame is decreased. Namely, the current bit budget for a current frame is reduced because the projected distortion under the current target bit rate for the frame will be less than by at least the threshold value as compared to at least three immediate previous frames of the same type. Thus, to reduce such a "valley" in distortion for the current frame, the bit budget is decreased for the current frame to limit the resources of the encoder i.e., to increase the distortion e.g., increase the size of the quantizer scale. If the query is negatively answered, then method 200 proceeds to step 240.

[0043] At step 240, method 200 queries whether a next frame is to be selected. If the query is positively answered, then method 200 proceeds to step 210 where the entire process starts again for the next frame. If the query is negatively answered, then method 200 proceeds to step 245 where the method ends.

[0044] It should be noted that it is possible that no adjustment is necessary. For example, the initial predicted bit budget may generate a picture quality measure that falls within "Th" and "Th'". This occurs where the query at step 220 is negatively answered, then method 200 proceeds to step 230. At step 230, the query is again negatively answered where no adjustment is made to the existing bit budget for the current frame.

[0045] FIG. 3 depicts an encoder 300 that incorporates an alternate embodiment of the present invention. The encoder contains a block motion compensator (BMC) and motion vector coder 304, subtractor 302, discrete cosine transform (DWT) coder 306, bit rate controller 310, DWT decoder 312 and output buffer 314.

[0046] In general, the input signal is a video image (a two-dimensional array of pixels (pels) defining a frame in a video sequence). To accurately transmit the image through a low bit rate channel, the spatial and temporal redundancy in the video frame sequence must be substantially reduced. This is generally accomplished by coding and transmitting only the differences between successive frames. The encoder has three functions: first, it produces, using the BMC and its coder 304, a plurality of motion vectors that represent motion that occurs between frames; second, it predicts the present frame using a reconstructed version of the previous frame combined with the motion vectors; and third, the predicted frame is subtracted from the present frame to produce a frame of residuals that are coded and transmitted along with the motion vectors to a receiver. Within the receiver, a decoder reconstructs each video frame using the coded residuals and motion vectors. A wavelet-based video encoder having the general structure of that depicted in FIG. 3 is disclosed in U.S patent 5,764,805, issued June 9, 1998, which is incorporated herein by reference. This issued patent discusses the use of wavelet transforms to encode video signals.

[0047] The discrete wavelet transform performs a wavelet hierarchical subband decomposition to produce a conventional wavelet tree representation of the input image. To accomplish such image decomposition, the image is decomposed using times two subsampling into high horizontal-high vertical (HH), high horizontal-low vertical (HL), low horizontal-high vertical (LH), and low horizontal-low vertical (LL), frequency subbands. The LL subband is then further subsampled times two to produce a set of HH, HL, LH and LL subbands. This subsampling is accomplished recursively to produce an array of subbands such as that illustrated in FIG. 4 where three subsamplings have been used. Preferably six subsamplings are used in practice. The parent-child dependencies between subbands are illustrated as arrows pointing from the subband of the parent nodes to the subbands of the child nodes. The lowest frequency subband is the top left LL₁, and the highest frequency subband is at the bottom right HH₃. In this example, all child nodes have one parent. A detailed discussion of subband decomposition is presented in J.M. Shapiro, "Embedded Image Coding Using Zerotrees of Wavelet Coefficients", IEEE Trans. on Signal Processing, Vol. 41, No. 12, pp. 3445-62, December 1993.

[0048] The DWT coder of FIG. 3 codes the coefficients of the wavelet tree in either a "breadth first" or "depth first" pattern. A breadth first pattern traverse the wavelet tree in a bit-plane by bit-plane pattern, i.e., quantize all parent nodes, then all children, then all grandchildren and so on. In contrast, a depth first pattern traverses each tree from the root in the low-low subband (LL_1) through the children (top down) or children through the low-low subband (bottom up).

[0049] This disclosure focuses on a technique for controlling the coding rate of an encoder, e.g., a wavelet encoder and a DCT encoder. Namely, the rate control method as discussed above can be implemented by the rate controller 310. of the wavelet encoder 300

[0050] FIG. 5 illustrates an encoding system 500 of the present invention. The encoding system comprises a general purpose computer 510 and various input/output devices 520. The general purpose computer comprises a central processing unit (CPU) 512, a memory 514 and an encoder 516 for receiving and encoding a sequence of images.

[0051] In the preferred embodiment, the encoder 516 is simply the encoder 100 and/or encoder 300 as discussed above. The encoder 516 can be a physical device which is coupled to the CPU 512 through a communication channel. Alternatively, the encoder 516 can be represented by a software application which is loaded from a storage device and resides in the memory 512 of the computer. As such, the encoder 100 and 300 of the present invention can be stored on a computer readable medium.

[0052] The computer 510 can be coupled to a plurality of input and output devices 520, such as a keyboard, a mouse, a camera, a camcorder, a video monitor, any number of imaging devices or storage devices, including but not limited to, a tape drive, a floppy drive, a hard disk drive or a compact disk drive. The input devices serve to provide inputs to the computer for producing the encoded video bit streams or to receive the sequence of video images from a storage device or an imaging device.

[0053] It should be noted that the present invention provides for two embodiments in the computation of the average quality measure D_{AVG} . In a first embodiment, the average quality measure may actually include the picture quality measure of the current frame, i.e., the quality measure of the current frame forms a part of the average measure. In a second embodiment, the average quality measure does not include the picture quality measure of the current frame, i.e., the quality measure of the current frame does not form a part of the average measure.

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217